NASA TECH BRIEF

NASA Pasadena Office



NASA Tech Briefs announce new technology derived from the U.S. space program. They are issued to encourage commercial application. Tech Briefs are available on a subscription basis from the National Technical Information Service, Springfield, Virginia 22151. Requests for individual copies or questions relating to the Tech Brief program may be directed to the Technology Utilization Office, NASA, Code KT, Washington, D.C. 20546.

Digital Data Command Bus


The problem:

To reduce the number of wire pairs required to communicate command data to systems and subsystems.

match specific impedance requirements.

Shield segments are joined by soldered jumper wires to reestablish the return path for the transformer primary current. The jumpers are disposed externally

Ferrite Plastic-Jacketed Core Coaxial Cable



The solution:

A command bus constructed from a coaxial cable that has short segments of its outer jacket and shield removed and replaced with small ferrite cores carrying multiturn windings connected to a decoder.

How it's done:

The diagram is a schematic representation of the way a coaxial cable, consisting of a central conductor and outer metallic shield separated by an insulating layer, is divided into segments by removal of the outer jacket and shield; the inner insulator is allowed to remain intact and linear ferrite cores are stationed at the open segments. A multiturn winding is disposed about the limb of the core as shown to form

to the cores so that shield current does not pass through the cores to affect transformer action. Alternatively, the shield current may be passed through the cores in reverse direction to enhance or aid the action of the primary current. The bus is excited by the constant voltage source (current driver) to transfer pulses at about a 10-volt level to each of the secondary windings. Typically, a signal of about 2 volts is developed when the secondary winding is appropriately loaded.

Termination Resistor

the secondary winding of a transformer; the central

conductor of the coaxial cable performs as a single-

turn primary for the ferrite core transformer. The winding may have as many turns as required to

The number of cores and windings placed on the bus corresponds to the number of systems and subsystems to be commanded. Each bus is terminated in

(continued overleaf)

This document was prepared under the sponsorship of the National Aeronautics and Space Administration. Neither the United States Government nor any person acting on behalf of the United States

Government assumes any liability resulting from the use of the information contained in this document, or warrants that such use will be free from privately owned rights.

its own characteristic impedance. If a parallel-bit decoding scheme is used, as many command buses would be required as there are bits in each command word. Thus, if each word were made up of four bits, four buses would be required. The secondary winding from each command bus would be connected to the appropriate input of each individual decoder for the particular system or subsystem.

Notes:

- 1. Performance and the effects of minor modifications have been checked on experimental models.
- Applications are suggested as a communication interface between not too distantly separated digital equipments and systems and as a means of minimizing some of the problems in computer interfacing.

3. Requests for further information may be directed to:

Technology Utilization Officer NASA Pasadena Office 4800 Oak Grove Drive Pasadena, California 91103 Reference: TSP 73-10035

Patent status:

NASA has decided not to apply for a patent.

Source: George C. Milligan of Caltech/JPL under contract to NASA Pasadena Office (NPO-11637)